

Level 1 Combiner Box

PV Combiner Box Level 1 to bundle the output lines of individual strings and to connect them to the inverter or optionally to a Level 2 Combiner Box.

Smart design customized for each customers application.

Advanced surge-protection devices, fuse links and switch disconnecter keep the correct operation and protection of the system.

Additionally, PV Combiner Box fulfill the standard IEC/EN 61439-2 to offer a high reliability on the units supplied.

- 24 string input
- fuse holders in string input (+/-) including fuse links
- surge protection device for DC system voltage
- string input with cable glands
- direct wall mount + plastic wall mount lugs



(Example of Combiner Box. Picture may differ from product)

PV 224S0F0V000TXPX10KO

Order reference 8000035449 Rev 2

Technical Data

APPLICATION DATA

Operating ambient temperature range	-25 °C to +45 °C
Intended installation location	protected outdoors (≤ 1 km from sea)
Degree of protection (acc. to IEC 60529)	IP65
Conformity with norms	IEC 61439-2 ed 2.0 / EN 61439-2:2011

ELECTRICAL CHARACTERISTICS

Rated DC voltage (Un)	1000 VDC
Rated DC current per input (Inc)	9.5 A at 45 °C ambient
Rated DC current per input (10h short-circuit at main output)	1.25 · Inc
Switch disconnecter breaking & making capacity (acc. to IEC 60947-3)	400 A (DC21B 1000 V)
Circuit breaker breaking & making capacity (acc. to IEC 60947-2)	N/A
Contactor breaking & making capacity (acc. to IEC 60947-4-1)	N/A
Switch-disconnector / Circuit breaker / Contactor handle location	direct handle (inside enclosure)
DC earthing system	floating positive and negative
Surge protection on DC ports	1000V DC, type II, I _{max} = 40 kA, U _p ≤ 4.0/4.0 kV, aux. contact

ENCLOSURE

Enclosure dimensions (H x W x D)	847 x 636 x 300 mm
Form factor	cabinet with hinged door(s)
Material	glass-fiber reinforced polyester (GFRP)
Fixing system	direct wall mount + plastic wall mount lugs

INPUTS

Number of DC inputs (+ & – being one input)	24
Positive DC input wires' to be connected to / cross-section (stranded)	screw connection / 0.75 - 25 mm ²
Negative DC input wires' to be connected to / cross-section (stranded)	screw connection / 0.75 - 25 mm ²
Positive / Negative DC input wires' outer diameter	5 - 10 mm
Fuses	fuse-links and fuse-disconnectors
Fuse form factor	10 x 38 mm
Location of fuses	positive and negative inputs
Fuse-link rated current (In)	15 A
Fuse-link time-current characteristic	gPV (EN 60269-6)
Earth wire to be connected to / cross-section (stranded)	screw connection / 2.5 - 35 mm ²
Earth wire outer diameter	6 - 12 mm

OUTPUTS

Number of DC outputs (+ & – being one output)	1
DC output wires' to be connected to / cross-section (stranded)	M10 bolt and nut connection / ≤ 240 mm ²
DC output wires' outer diameter	18 - 25 mm

OTHERS

Notes	Waterproof combiner box acc. IP65
	Relativity Humidity: up to 95% non-condensating
	Fuse holders with led